

Generation and Propagation of Nonlinear Waves in Travelling Wave Tubes

Stephan I. Tzenov*

*Dipartimento di Fisica "E.R. Caianiello", Università degli Studi di Salerno and INFN Sezione di Napoli
Gruppo Collegato di Salerno, Via S. Allende, I-84081 Baronissi (SA), Italy*

(Dated: February 2, 2008)

The generation and evolution of nonlinear waves in microwave amplifiers such as travelling wave tubes, free electron lasers and klystrons have been studied. The analysis is based on the hydrodynamic and field equations for the self-consistent evolution of the beam density distribution, the current velocity and the electromagnetic fields. A system of coupled nonlinear Schrödinger equations for the slowly varying amplitudes of interacting beam-density waves has been derived. Under the approximation of an isolated mode neglecting the effect of the rest of the modes, this system reduces to a single nonlinear Schrödinger equation for that particular mode.

PACS numbers: 84.40.Fe, 52.59.Rz, 41.60.Cr.

KEY WORDS: Microwave Amplifier, Renormalization Group, Solitary Waves.

I. INTRODUCTION

The generation and evolution of nonlinear waves and harmonic distortions in microwave amplifiers such as travelling wave tubes, free electron lasers (FELs) and klystrons have recently attracted much research interest [1, 2, 3]. In connection with the construction and commissioning of the next generation of FELs and powerful klystrons for accelerating RF cavities in circular machines and linear colliders, this issue has become even more challenging. Of particular importance are the effects of intense self-fields due to space charge and current, as well as wake fields due to interaction impedances. Both of the above influence the propagation of the electron beam in microwave devices, its stability and transport properties. In general, a complete description of collective processes in intense charged particle beams is provided by the Vlasov-Maxwell equations for the self-consistent evolution of the beam distribution function and the electromagnetic fields. Usually, the electron beam in a travelling wave tube can be assumed to be weakly collisional. Hence, the dynamics of electrons is well described by the hydrodynamic equations coupled with the equations for the electromagnetic self-fields, which constitutes a substantial simplification of the model. Although the analytical basis for modelling the dynamics and behaviour of space-charge-dominated beams is well established, a thorough and satisfactory understanding of collective processes, detailed equilibrium and formation of patterns and coherent structures is far from being complete.

While the linear theory of wave generation in microwave amplifiers is relatively well understood [4], the nonlinear regime is far from being exhaustively studied. The present paper is aimed at filling this gap. We will be mainly interested in describing the slow evolution of some coarse-grained quantities that are easily measur-

able, such as the wave amplitudes. Owing to the nonlinear wave interaction contingent on the nonlinear coupling between the hydrodynamic and Maxwell equations, one can expect a formation of nontrivial coherent structure that might be fairly stable in space and time [5, 6]. Here, we show that solitary wave patterns in the electron beam density distribution are an irrevocable feature, characteristic of powerful microwave amplifiers.

The paper is organized as follows. In the next section, we state the basic equations which will be the subject of the renormalization group (RG) reduction in section III. Starting from a single equation [see equation (20)] for the density distribution of the electron beam, we obtain a formal perturbation expansion of its solution to second order. As expected, it contains secular terms proportional to powers of the time variable which is the only renormalization parameter adopted in our approach. In section IV, the arbitrary constant amplitudes of the perturbation expansion are renormalized such as to eliminate the secular terms. As a result, a set of equations for the renormalized slowly varying amplitudes is obtained, known as the renormalization group equations (RGEs). These equations comprise an infinite system of coupled nonlinear Schrödinger equations. Finally, section V is dedicated to discussion and conclusions.

II. FORMULATION OF THE PROBLEM AND BASIC EQUATIONS

The electron beam in a travelling wave tube is assumed to be weakly collisional. Therefore, the dynamics of electrons is well described by the hydrodynamic equations coupled with the equations for the electromagnetic self-fields. We start with the 1D description of a beam of electrons propagating in an external focusing electric field with focusing coefficient G , which models the bunching of the electron beam in the longitudinal direction. As we will see in the sequel its additional role is to attain a sta-

*Electronic address: tzenov@sa.infn.it

tionary equilibrium by partially compensating the space-charge defocusing. The continuity and the momentum balance equations can be written as

$$\frac{\partial \varrho}{\partial t} + \frac{\partial}{\partial z}(\varrho v) = 0, \quad (1)$$

$$\frac{\partial v}{\partial t} + v \frac{\partial v}{\partial z} = -Gz - \frac{k_B T}{m \varrho} \frac{\partial \varrho}{\partial z} - \frac{e}{m} \left(\frac{\partial \varphi_{sc}}{\partial z} + \frac{\partial \varphi_w}{\partial z} \right), \quad (2)$$

where ϱ and v are the electron density and the current velocity. Furthermore, m , e and T are the mass, the charge and the temperature, respectively, while k_B is the Boltzmann constant. The space-charge φ_{sc} and wave φ_w potentials satisfy the Poisson and the wave equation

$$\frac{\partial^2 \varphi_{sc}}{\partial z^2} = -\frac{en\varrho}{\varepsilon_0}, \quad (3)$$

$$\square \varphi_w = -\frac{enAZ_0}{c} \frac{\partial^2 \varrho}{\partial t^2}, \quad \square = \frac{\partial^2}{\partial z^2} - \frac{1}{c^2} \frac{\partial^2}{\partial t^2}, \quad (4)$$

where $\square$ denotes the well-known d'Alembert operator. In addition, ε_0 is the permittivity of free space and $n = N_e/V_t$ is the electron number density, where N_e is the total number of electrons and V_t is the volume occupied by the electron beam in the longitudinal direction. Moreover, the electron beam cross-sectional area is represented by A , the quantity Z_0 denotes the interaction impedance, while c represents the phase velocity of a cold circuit wave.

Let us introduce the scaling

$$\varphi_{sc} = \frac{en}{\varepsilon_0} U_{sc}, \quad \varphi_w = \frac{en}{\varepsilon_0} W, \quad (5)$$

and rewrite equations (2)–(4) as follows

$$\frac{\partial v}{\partial t} + v \frac{\partial v}{\partial z} = -Gz - \frac{v_T^2}{\varrho} \frac{\partial \varrho}{\partial z} - \omega_p^2 \left(\frac{\partial U_{sc}}{\partial z} + \frac{\partial W}{\partial z} \right), \quad (6)$$

$$\frac{\partial^2 U_{sc}}{\partial z^2} = -\varrho, \quad \square W = -\mathcal{Z} \frac{\partial^2 \varrho}{\partial t^2}. \quad (7)$$

The electron plasma frequency ω_p and the thermal velocity v_T of the electron beam are expressed according to

$$\omega_p^2 = \frac{e^2 n}{\varepsilon_0 m}, \quad v_T^2 = \frac{k_B T}{m}, \quad (8)$$

while

$$\mathcal{Z} = \frac{\varepsilon_0 Z_0 A}{c}, \quad (9)$$

is a shorthand parameter introduced for later convenience. Note that the thermal velocity v_T as defined by

equation (8) can be alternatively expressed according to the relation

$$v_T = \omega_p r_D, \quad r_D^2 = \frac{\varepsilon_0 k_B T}{e^2 n_0}, \quad (10)$$

where r_D is the electron Debye radius. Equations (1), (6) and (7) possess a stationary equilibrium solution

$$\varrho_0 = \frac{G}{\omega_p^2}, \quad v_0 = 0, \quad U_0 = -\frac{Gz^2}{2\omega_p^2}, \quad W_0 = 0. \quad (11)$$

Therefore, we can further scale the hydrodynamic and field variables as

$$\varrho = \varrho_0 + \epsilon R, \quad U_{sc} = U_0 + \epsilon U, \quad v \rightarrow \epsilon v, \quad W \rightarrow \epsilon W, \quad (12)$$

where ϵ is a formal small parameter introduced for convenience, which will be set equal to one at the end of the calculations. Thus, the basic equations to be used for the subsequent analysis can be written in the form

$$\frac{\partial R}{\partial t} + \varrho_0 \frac{\partial v}{\partial z} + \epsilon \frac{\partial}{\partial z}(Rv) = 0, \quad (13)$$

$$\frac{\partial v}{\partial t} + \epsilon v \frac{\partial v}{\partial z} = -\frac{v_T^2}{\varrho_0 + \epsilon R} \frac{\partial R}{\partial z} - \omega_p^2 \left(\frac{\partial U}{\partial z} + \frac{\partial W}{\partial z} \right), \quad (14)$$

$$\frac{\partial^2 U}{\partial z^2} = -R, \quad \square W = -\mathcal{Z} \frac{\partial^2 R}{\partial t^2}. \quad (15)$$

Before we continue with the renormalization group reduction of the system of equations (13)–(15) in the next section, let us assume that the actual dependence of the quantities R , v , U and W on the spatial variables is represented by the expression

$$\hat{\Psi} = \hat{\Psi}(z, \xi; t), \quad \hat{\Psi} = (R, v, U, W), \quad (16)$$

where $\xi = \epsilon z$ is a slow spatial variable. Thus, the only renormalization parameter left at our disposal is the time t which will prove extremely convenient and simplify tedious algebra in the sequel.

III. RENORMALIZATION GROUP REDUCTION OF THE HYDRODYNAMIC EQUATIONS

Following the standard procedure of the renormalization group method, we represent $\hat{\Psi}$ as a perturbation expansion

$$\hat{\Psi} = \sum_{n=0}^{\infty} \epsilon^n \hat{\Psi}_n, \quad (17)$$

in the formal small parameter ϵ . The next step consists in expanding the system of hydrodynamic and field equations (13)–(15) in the small parameter ϵ , and obtaining

their naive perturbation solution order by order. It is possible to simplify this system, which will turn out extremely useful in what follows. Differentiating equation (13) with respect to the time t , differentiating equation (14) with respect to z and using equations (15), we can eliminate the electric potentials. As a result of obvious manipulations, we obtain

$$\begin{aligned} \hat{\mathcal{L}}R = \epsilon \square \left[\frac{\rho_0}{2} \frac{\partial^2}{\partial z^2} (v^2) - \frac{\partial^2}{\partial t \partial z} (Rv) \right] \\ + v_T^2 \square \frac{\partial^2}{\partial z^2} \left[\frac{\rho_0}{\epsilon} \ln \left(1 + \frac{\epsilon R}{\rho_0} \right) - R \right], \end{aligned} \quad (18)$$

where the linear differential operator $\hat{\mathcal{L}}(\partial_z, \partial_t)$ is given by the expression

$$\hat{\mathcal{L}}(\partial_z, \partial_t) = \square \left(\frac{\partial^2}{\partial t^2} - v_T^2 \frac{\partial^2}{\partial z^2} + G \right) + GZ \frac{\partial^4}{\partial t^2 \partial z^2}. \quad (19)$$

Taking into account the expansion of the logarithm, we notice that the right-hand-side of equation (18) is at least of first order in the formal parameter, so that

$$\begin{aligned} \hat{\mathcal{L}}R = \epsilon \square \left[\frac{\rho_0}{2} \frac{\partial^2}{\partial z^2} (v^2) - \frac{\partial^2}{\partial t \partial z} (Rv) \right] \\ - \epsilon v_T^2 \square \frac{\partial^2}{\partial z^2} \left(\frac{R^2}{2\rho_0} - \frac{\epsilon R^3}{3\rho_0^2} + \frac{\epsilon^2 R^4}{4\rho_0^3} - \dots \right), \end{aligned} \quad (20)$$

Equation (20) represents the starting point for the renormalization group reduction, the final goal of which is to obtain a description of the relatively slow dynamics leading to formation of patterns and coherent structures.

Let us proceed order by order. The solution to the zero-order perturbation equation (20) can be written as

$$R_0(z, \xi; t) = \sum_k A_k(\xi) e^{i\psi_k(z; t)}, \quad (21)$$

where

$$\psi_k(z; t) = kz - \omega_k t, \quad (22)$$

and A_k is an infinite set of constant complex amplitudes, which will be the subject of the renormalization procedure in the sequel. Here "constant" means that the amplitudes A_k do not depend on the fast spatial variable z and on the time t , however, they can depend on the slow spatial variables ξ . The summation sign in equation (21) and throughout the paper implies summation over the wave number k in the case where it takes discrete values, or integration in the continuous case. From the dispersion equation

$$\mathcal{D}(k; \omega_k) = GZk^2\omega_k^2 - \square_k(\omega_k^2 - k^2v_T^2 - G) = 0, \quad (23)$$

it follows that the wave frequency ω_k can be expressed in terms of the wave number k , where the Fourier-image

$\square_k$ of the d'Alembert operator can be written according to

$$\square_k = \frac{\omega_k^2}{c^2} - k^2. \quad (24)$$

It is important to emphasize that

$$\omega_{-k} = -\omega_k, \quad A_{-k} = A_k^*, \quad (25)$$

where the asterisk denotes complex conjugation. The latter assures that the perturbed density distribution as defined by equation (21) is a real quantity. The zero-order current velocity $v_0(z, \xi; t)$ obtained directly from equation (13) can be written as

$$v_0(z, \xi; t) = \sum_k v_k^{(0)} A_k(\xi) e^{i\psi_k(z; t)}, \quad v_k^{(0)} = \frac{\omega_k}{\rho_0 k}. \quad (26)$$

In first order equation (20) acquires the form

$$\hat{\mathcal{L}}R_1 + \hat{\mathcal{L}}_z \frac{\partial R_0}{\partial \xi} = \square \left[\frac{\rho_0}{2} \frac{\partial^2 v_0^2}{\partial z^2} - \frac{\partial^2}{\partial t \partial z} (R_0 v_0) - \frac{v_T^2}{2\rho_0} \frac{\partial^2 R_0^2}{\partial z^2} \right], \quad (27)$$

where by $\hat{\mathcal{L}}_z$ we have denoted the derivative of the operator $\hat{\mathcal{L}}$ with respect to ∂_z . It has now two types of solutions. The first is a secular solution linearly dependent on the time variable in the first-order approximation. As a rule, the highest power in the renormalization parameter of the secular terms contained in the standard perturbation expansion is equal to the corresponding order in the small perturbation parameter. The second solution of equation (20) arising from the nonlinear interaction between waves in the first order, is regular. Taking into account the fact that the Fourier image of the operator $\hat{\mathcal{L}}_z$ is equal to $-i(\partial \mathcal{D} / \partial k)$, we can write the equation for determining of the secular part of the solution as

$$\hat{\mathcal{L}}R_1^{(s)} = i \sum_k \frac{\partial \mathcal{D}}{\partial k} \frac{\partial A_k}{\partial \xi} e^{i\psi_k}. \quad (28)$$

We note further that

$$\hat{\mathcal{L}}t e^{i\psi_k} = t \mathcal{D} e^{i\psi_k} + i \frac{\partial \mathcal{D}}{\partial \omega_k} e^{i\psi_k} = i \frac{\partial \mathcal{D}}{\partial \omega_k} e^{i\psi_k}, \quad (29)$$

which is a direct consequence of the general relation

$$\hat{\mathcal{L}}t G(t) = t \hat{\mathcal{L}}G(t) + \hat{\mathcal{L}}_t G(t), \quad (30)$$

holding for a generic function $G(t)$. Here $\hat{\mathcal{L}}_t$ implies differentiation with respect to ∂_t . To verify equation (30), it suffices to prove the identity by induction in the case, where $\hat{\mathcal{L}}$ is the monomial operator ∂_t^n and then take into account the Taylor expansion of $\hat{\mathcal{L}}$. With these remarks in hand, it is straightforward to solve equation (28). Combining its solution with the solution of the regular part, we obtain

$$R_1 = -t \sum_k u_{gk} \frac{\partial A_k}{\partial \xi} e^{i\psi_k} - \frac{1}{2\rho_0} \sum_{k,l} \alpha_{kl} A_k A_l e^{i(\psi_k + \psi_l)}, \quad (31)$$

where u_{gk} is the group velocity defined as

$$u_{gk} = \frac{d\omega_k}{dk} = -\frac{\partial \mathcal{D}}{\partial k} \left(\frac{\partial \mathcal{D}}{\partial \omega_k} \right)^{-1}. \quad (32)$$

In explicit form, the components of the infinite matrix α_{kl} are given by the expression

$$\alpha_{kl} = \frac{\gamma_{kl}}{\mathcal{D}_{kl}}, \quad (33)$$

where

$$\gamma_{kl} = \square_{kl}(k+l)$$

$$\times \left[(\omega_k + \omega_l) \left(\frac{\omega_k}{k} + \frac{\omega_l}{l} \right) - (k+l) \left(v_T^2 - \frac{\omega_k \omega_l}{kl} \right) \right], \quad (34)$$

$$\square_{kl} = \frac{(\omega_k + \omega_l)^2}{c^2} - (k+l)^2, \quad (35)$$

$$\mathcal{D}_{kl} = \mathcal{D}(k+l, \omega_k + \omega_l). \quad (36)$$

Furthermore, the first-order current velocity can be expressed as

$$v_1 = \sum_k v_k^{(1)} \frac{\partial A_k}{\partial \xi} e^{i\psi_k} - \frac{1}{2\varrho_0^2} \sum_{k,l} \beta_{kl} A_k A_l e^{i(\psi_k + \psi_l)}, \quad (37)$$

where

$$v_k^{(1)} = -u_{gk} v_k^{(0)} t - \frac{i}{\varrho_0 k} \left(u_{gk} - \varrho_0 v_k^{(0)} \right), \quad (38)$$

$$\beta_{kl} = \frac{\omega_k}{k} + \frac{\omega_l}{l} + \alpha_{kl} \frac{\omega_k + \omega_l}{k+l}, \quad \beta_{k,-k} = 0. \quad (39)$$

A couple of interesting features of the zero and first-order perturbation solution are noteworthy to be commented at this point. First of all, the zero-order density, current velocity (and electric potentials) are proportional to the arbitrary complex amplitudes A_k . The second terms in the expressions for the first-order density R_1 and current velocity v_1 [see equations (31) and (37)] imply contribution from nonlinear interaction between waves. It will be shown in the remainder that these terms give rise to nonlinear terms in the renormalization group equation and describe solitary wave behaviour of a generic mode.

IV. THE RENORMALIZATION GROUP EQUATION

Passing over to the final stage of our renormalization group procedure, we note that particular terms in the

second-order perturbation equation (20) will contribute to the secular solution. Since we are interested in this solution to be renormalized later, the contributing terms will be retained only. Hence, we can write

$$\begin{aligned} \hat{\mathcal{L}} R_2 + \hat{\mathcal{L}}_z \frac{\partial R_1}{\partial \xi} + \frac{\hat{\mathcal{L}}_{zz}}{2} \frac{\partial^2 R_0}{\partial \xi^2} = \square \left[\varrho_0 \frac{\partial^2 (v_0 v_1)}{\partial z^2} \right. \\ \left. - \frac{\partial^2}{\partial t \partial z} (R_0 v_1 + R_1 v_0) - \frac{v_T^2}{\varrho_0} \frac{\partial^2 (R_0 R_1)}{\partial z^2} + \frac{v_T^2}{3\varrho_0^2} \frac{\partial^2 R_0^3}{\partial z^2} \right], \end{aligned} \quad (40)$$

or in explicit form

$$\begin{aligned} \hat{\mathcal{L}} R_2 = \sum_k \left[u_{gk} \left(-it \frac{\partial \mathcal{D}}{\partial k} + \frac{\partial^2 \mathcal{D}}{\partial k \partial \omega_k} \right) + \frac{1}{2} \frac{\partial^2 \mathcal{D}}{\partial k^2} \right] \frac{\partial^2 A_k}{\partial \xi^2} e^{i\psi_k} \\ + \frac{1}{\varrho_0^2} \sum_{k,m} \Gamma_{mk} |A_m|^2 A_k e^{i\psi_k}. \end{aligned} \quad (41)$$

The components of the infinite matrix Γ_{mk} can be expressed according to the relation

$$\begin{aligned} \Gamma_{mk} = \square_k k^2 \left[\beta_{mk} \left(\frac{\omega_m}{m} + \frac{\omega_k}{k} \right) \right. \\ \left. - \alpha_{mk} \left(v_T^2 - \frac{\omega_m \omega_k}{mk} \right) - v_T^2 \right]. \end{aligned} \quad (42)$$

A standard algebra similar to the one outlined in the previous section leads to the second order secular solution

$$\begin{aligned} R_2 = \sum_k \left(\frac{u_{gk}^2 t^2}{2} + \frac{G_k t}{2i} \right) \frac{\partial^2 A_k}{\partial \xi^2} e^{i\psi_k} \\ + \frac{t}{i\varrho_0^2} \sum_{k,m} \Gamma_{mk} \left(\frac{\partial \mathcal{D}}{\partial \omega_k} \right)^{-1} |A_m|^2 A_k e^{i\psi_k}, \end{aligned} \quad (43)$$

where

$$G_k = \left(u_{gk}^2 \frac{\partial^2 \mathcal{D}}{\partial \omega_k^2} + 2u_{gk} \frac{\partial^2 \mathcal{D}}{\partial k \partial \omega_k} + \frac{\partial^2 \mathcal{D}}{\partial k^2} \right) \left(\frac{\partial \mathcal{D}}{\partial \omega_k} \right)^{-1}. \quad (44)$$

Taking into account the definition (32) of the group velocity, we conclude that

$$\frac{du_{gk}}{dk} = \frac{\partial u_{gk}}{\partial k} + u_{gk} \frac{\partial u_{gk}}{\partial \omega_k} = -G_k. \quad (45)$$

Following the standard procedure [5, 6, 7] of the RG method, we finally obtain the desired RG equation

$$i \frac{\partial \tilde{A}_k}{\partial t} + i u_{gk} \frac{\partial \tilde{A}_k}{\partial z}$$

$$= \frac{G_k}{2} \frac{\partial^2 \tilde{A}_k}{\partial z^2} + \frac{1}{\varrho_0^2} \left(\frac{\partial \mathcal{D}}{\partial \omega_k} \right)^{-1} \sum_m \Gamma_{mk} |\tilde{A}_m|^2 \tilde{A}_k, \quad (46)$$

where now $\tilde{A}_k$ is the renormalized complex amplitude [5]. Thus, the renormalized solution for the density perturbation of the electron beam acquires the form

$$R(z; t) = \sum_k \tilde{A}_k(z; t) e^{i\psi_k(z; t)}, \quad (47)$$

For the renormalized electric field, we obtain

$$E(z; t) = \frac{ien}{\epsilon_0 G} \sum_k \frac{k^2 v_T^2 - \omega_k^2}{k} \tilde{A}_k(z; t) e^{i\psi_k(z; t)}, \quad (48)$$

Equations (46) represent a system of coupled nonlinear Schrödinger equations for the amplitudes of eigenmodes. Consider a particular mode with a wave number k . As a first approximation, the contribution of the other modes with $m \neq k$ can be neglected, which results in a single nonlinear Schrödinger equation for mode k . The nonlinearity in the corresponding nonlinear Schrödinger equation describes the nonlinear interaction of the mode k with itself.

It should be emphasized that the approach outlined in the present paper is rather general even in the case of more than one renormalization parameter, where the extension should be straightforward. Note that the unique assumption concerns the knowledge of the dispersion properties of the linear differential operator governing the evolution of the zero-order quantities. The

approach can be successfully applied to a wide class of problems of particular physical interest.

V. DISCUSSION AND CONCLUSIONS

We have studied the generation and evolution of nonlinear waves in microwave amplifiers such as travelling wave tubes, free electron lasers and klystrons. The analysis performed in the present paper is based on the hydrodynamic and field equations for the self-consistent evolution of the beam density distribution, the current velocity and the electromagnetic fields. Using further the RG method, a system of coupled nonlinear Schrödinger equations for the slowly varying amplitudes of interacting beam-density waves has been derived. Under the approximation of an isolated mode neglecting the effect of the rest of the modes, this system reduces to a single nonlinear Schrödinger equation for that particular mode.

Since the approach pursued here is rather general, it is presumed that it may find applications to other problems, where of particular interest is the dynamics of slowly varying amplitudes of patterns and coherent structures.

Acknowledgments

It is a pleasure to thank R.C. Davidson for many interesting and useful discussions concerning the subject of the present paper.

-
- [1] J.G. Wöhlbier, I. Dobson and J.H. Booske, Phys. Rev. E, **66**, 056504 (2002).
 - [2] H.P. Freund, S.G. Biedron and S.V. Milton, IEEE Journal of Quantum Electronics, **36**, 275 (2000).
 - [3] R. Bonifacio, F. Casagrande and L. De Salvo Souza, Phys. Rev. A **33**, 2836 (1986).
 - [4] J.G. Wöhlbier, J.H. Booske and I. Dobson, IEEE Transactions on Plasma Science, **30**, 1063 (2002).
 - [5] S.I. Tzenov, *Contemporary Accelerator Physics* (World Scientific, Singapore, 2004).
 - [6] S.I. Tzenov, New J. Phys., **6**, 19 (2004).
 - [7] L.Y. Chen, N. Goldenfeld and Y. Oono, Phys. Rev., **E 54**, 376 (1996).